

Input

Input voltage range	185- 264VAC, 40-70Hz (other frequencies possible. Please ask for)
Inrush current	max. 70ADC, limited by 5Ω - NTC
Fuse	25 AT or MCB 20A characteristic K externally
No load input current	ca. 200mA at 230VAC
Switch on delay time	2s
Hold up time	>10ms at 230VAC and nominal output load
Turn on	> 175VAC
Turn off	< 175VAC / > 275VAC
Spikes	acc. EN 61000-4-5, Class 3
Bursts	acc. EN 61000-4-4, Level 3

Output

Output voltage	for 110VDC battery (programmable by factory from 110VDC to 150VDC depending on battery type)
Output current	13ADC
Charging characteristic	programmable by factory for several application (for example temperature-controlled characteristic, boost charge and other)
Line regulation, Load regulation	±2%, measured directly at the connection terminal
Ripple	< 1100mV p-p typ without battery
Response time	typ. 2ms
Load transient 10-100-10%	typ. 6%
On/off overshoot	none
Overload protection	electronically
Over voltage protection	> 165VDC switch off, not automatic return, no effect on external over voltage
Sense lines	internally connected (optional on connector)
Parallel-/redundant Connection	active ORing decoupling.
Active current sharing	using the active current sharing in a parallel connection, the communication between the units is done by the use of a current share bus. Thereby a current symmetry off < 5% lout nom. can be achieved. It's possible to connect up to 8 units in parallel.
LED`s	the green LED Uin at front is lightning if input voltage is ok., (the LED is flashing if input voltage is ok. but the primary inhibit is open) the green LED Uout at front is lightning if output voltage is ok., (the LED is flashing if input voltage is ok. but the 24VDC inhibit is active) the red LED Failure is lightning if unit fails (see description alarm)
Alarm Signals	over potential free relay contacts NOC/NCC rating max. 250VDC; 0,5ADC or 264VAC; 3AAC interface IO-Link optional (alarm by failures: input voltage out of tolerance, overtemperature, internal over voltage (OVP active), overload at output, unit fails).
Battery and -circuit	at startup and when battery current is lower than the defined value for 2 hours, output voltage is increased to a higher defined value for 1 second (no alarm if no other error is detected) - if charging current now does not rise, alarm is set. - if charging current rise for at least 0.5 sec. the alarm output is reset. the defined values for the current are depending from type of unit

Inhibit

- primary
for turn on the unit, contacts 3 and 4 on connector X1 must be closed by switch or wire.
(Connection is made by factory. For use primary inhibit, remove the connection and add for example a switch)

Attention

no galvanic isolation, **connected with Input**,
On / Off levels contacts 3 and 4 closed - unit "On" output voltage is normal
 contacts 3 and 4 open - unit "Off" out voltage 0VDC

-Inhibit 24VDC (Connector X2)

digital input, Unom. 24VDC

galvanic isolated 750 VAC and 1000 VDC permanently

connector 2-wire

on / off levels signal "0": 0-5VDC; output voltage is normal

 signal "1": 15-30VDC; output voltage 0VDC

Input impedance 1200Ω, input current max 25mA

General

Operating temperature	-25°C to +55°C
Current derating	automatically from +55°C to +75°C about 2,5%/°C with a free convection.
Over temperature protection	unit switch off if internally temperature is too high, automatically switch on after cooling
Storage temperature	-40°C to +85°C
Humidity	75% without condensation,
Efficiency at full load	>90%,
Power dissipation	app. 200W
Over temperature protection	shut off, at hot spot off about 100°C. Automatically restart after cooling down.
Construction	EN 61010 I
Isolation	acc. EN 50178, EN 60950
RFI-interference	acc. EN 55011 Class "A"
EMC / CE	EN 61000-6-4, EN 61000-6-2 Grounding of input and/or output potentials and/or connecting input to output may cause changes of EMC and/or ripple values.
Protection class	I acc. EN 61140
Visual Indications	green LED U _{in} = Input voltage on green LED U _{out} = Output voltage ok (DC ok.)
Case	for chassis mount Ip20
Connection	plug-in terminals on front panel
Weight	app. 10kg